

Endless Music

The four powered stereo outputs deliver an enviable 30 watts per room, simply add more Mini4's to expand up to 32 rooms. This is a hidden audio system that can fill your world with music.

One Optical and one RCA input via the Baltx2 and one additional RCA input on the Mini4 connects your favorite devices so you can hear them everywhere along with two configurable Digital Input or Output connections. The Mini4 also has one Airplay Stream.

When used in conjunction with the AX-AMM Media Manager, internet streaming sources lets you play music from thousands of internet radio stations from TuneIn Radio, listen to Spotify Connect, Tidal or from your mobile device, even from network attached storage, all controlled by the free auto discovery app (iOS and Android) or keypads that put you in control.

Unrivalled Control

The internal webpage has all the customization needed to control and configure the system the way you like it. The **FREE** app (iOS and Android) auto discovers the Amplifier so there is no complex setup.

Two keypad ports allow for wall mounted keypads to control your system or use the KPC-N 2.8" wall mounted color touchscreen where all zones can be controlled.

Audio Control

Adjustable Bass, Treble, Balance, Loudness and audio delay fine tunes your system to your exacting needs.

Prepare to be spellbound in as many rooms as you need....



BALTX2 supplied with the Mini4



Technical Specifications

- 15 Watts per channel. 30 Watts per Zone @8Ω
 - Fully implemented UPNP server and discovery functionality
 - Output short circuit, thermal and hard clipping protection
 - 1 x Airplay Stream
 - 5 Source inputs:
 - 1 x local RCA source input
 - 1 x Balanced RCA input (via the BALTX2)
 - 1 x Optical source input (via the BALTX2)
 - 2 x Configurable Digital input/outputs
 - Expandable to 96 zones
 - 4 Band parametric EQ
 - Bass, Treble, Balance Loudness adjustments per zone
 - Two keypad ports for in room keypad control
- Internal Web Page with user control and setup pages.
 - FREE app** for both iOS and Android systems
 - 600ms of adjustable audio delay per zone
 - IR output for control of local 3rd party devices**
 - Zone linking features
 - Static and DHCP network capability
 - External 15v DC Power Supply
 - Dimensions: 165mm x 147mm x 35mm

*** Recommended configuration by Custom Installation Professional using ADP*

Specifications and features subject to change without notice. Please check www.axiumcontrol.com for latest updates



Axium

Unit 14, 49 Sainsbury Rd, Morningside, Auckland, New Zealand

P: +64 (9) 3774600

E: sales@axium.co.nz

www.axiumcontrol.com