
VGA Splitter VSA-12 / VSA-14 / VSA-18



VGA Splitters, broadcast and boost one VGA signal source for 2, 4, or 8 VGA monitors. There is no software or interface card to install. Simply connect the cables, power up the system and you are ready to duplicate VGA images to multiple monitors with excellent clarity. Superb high bandwidth circuit enables a high-resolution VGA signal of 350 MHz to be displayed on multiple monitors.

Connection Pattern

Available colors:



Features

- Duplicate one VGA input to multiple VGA outputs
- Effective transmission distance: 65M (210ft)with UL-2919 rated VGA cables
- Automatic power-save when VGA input is lost
- Applicable to VGA, SVGA and multi-sync monitors
- · Cascaded operation for increased VGA outputs
- Crisp clear VGA images

Specifications

| | | VSA-12 | VSA-14 | VSA-18 |
|---------------------------|--------|--|------------------|------------------|
| Number of VGA Output | | 2 | 4 | 8 |
| Signal Bandwidth | | 350MHz | | 300MHz |
| Signal Type | | VGA, SVGA, Multi-Sync | | |
| LED Indicators | | Power (Green) x 1 Active (Amber) x 1 | | |
| Cable Length | | 65M (210ft) Max. | | |
| Connectors | Input | HDB15 Male x 1 | | |
| | Output | HDB15 Female x 2 | HDB15 Female x 4 | HDB15 Female x 8 |
| Enclosure | | Metal | | |
| Weight (g) | | 400 | 428 | 720 |
| Power Consumption (Max.) | | AC 9V, 200mA Normal Operation 10mA, Power-Save Mode | | |
| Dimensions H x W x D (mm) | | 20 x 85 x 180 | | 44 x 196 x 70 |